

In the box:

- Ceiling plate kit and electrical fittings
- Noctis Urchin Small pendants x 3
- Installation instructions

Only qualified persons should assemble the luminaire. If in doubt, consult a suitably qualified person. Installation MUST be carried out in accordance and compliance with current building regulations

1. Ensure the electrical supply is turned OFF.

2. Using an adjustable spanner and pozidriv screwdriver, loosen and adjust the position of the mounting bolts on the ceiling plate bracket to correspond with the pre drilled holes on the ceiling plate. Tighten the nuts to secure the bolts in the correct position.

3. Identify where the supply cable is to avoid damage to concealed wiring during installation. Determine the fixing method appropriate to the ceiling structure and secure the plate bracket to the ceiling, ensuring it is secured to a suitably strong joist or beam.

4. Before attaching the ceiling plate to the bracket, each pendant should be adjusted to the desired drop height. Using a small flat head screwdriver, loosen the grub screw in the cord grip at the top of each pendant drop. Excess wire can either be cut (and rewired) or carefully coiled into the recess of the ceiling plate. Tighten the grub screws to securely hold each of the pendants at the chosen height. Support the ceiling plate so that no strain is applied to the wiring when making the electrical connections. If necessary get a colleague to help.

5. Once the pendant drops are adjusted to the desired height and the electrical connection is made, hand tighten the decorative nuts onto the ceiling plate bracket bolts to securely hold the fitting in place.

6. Carefully attach each Noctis Urchin shade to the bulb holders. Avoid touching the brass plates on the lampshade too much as fingerprints may start to show. Fit a suitable light bulb to each shade. **Max 25 LED Watt.**

7. Turn the power supply on to complete installation.

*** If the external flexible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer or his service agent or a similar qualified person in order to avoid a hazard. ***