

10W On-Desk Charger | TA-8200



Table of Contents

Introduction	2
Package Contents	2
Important Safety Instructions	3
Mounting and Installation	4
Usage	5
Specifications	5

Introduction

Thank you for purchasing the 10W On-Desk Wireless Charger. Please read these instructions carefully before using this product and keep this manual for future reference.

The 10W On-Desk Wireless Charger (TA-8200-US-A00) is a high-performance device which is suitable for charging compatible mobile phones and other devices that support Qi. Wireless charging at 10W and 5W is supported.

A range of mounting options are supplied including a bracket, a lanyard and an adhesive pad. For safety, foreign object detection (FOD) is supported with an intelligent two-color status indicator which confirms when a device is successfully charging or if a foreign object has been detected.

The 10W On-Desk Wireless Charger is Qi Certified and FCC/CE compliant.

Package Contents

- 10W On-Desk Wireless Charger unit, black.
- QC 3.0 wall charger with US plug.
- USB-A to Micro USB cable, 1.5M, black.
- Mounting bracket with rubber pad, black.
- 3M double sided adhesive pad, black.
- Security lanyard.
- Screws (4xM2.3x6mm, 1xM2.5x3mm, 1xM3x15mm).
- Wall fixing plug.
- User manual.

Important Safety Instructions

- Always use the wireless charger in accordance with the instructions in this user manual.
- Use the supplied power adapter and USB cable.
- Unplug the wireless charger after use.
- Do not use the wireless charger with devices that are not Qi Certified.
- It is normal that the wireless charger may get a little warm during use.
- The wireless charger will not charge any devices that do not conform to the Qi specification. In this case remove the non-conformant device.
- Do not install wireless charger close to a heat source such as a radiator or in direct sunlight.
- Do not expose the wireless charger near sources of liquid like a sink, basin, bath or shower.
- Do not use corrosive or abrasive cleaners on the wireless charger.

Mounting and Installation

Choose the mounting option that best meets your needs. Make sure you mount within reach of a suitable mains outlet.

1. Bracket secured to desk.

1. Plug USB cable into the charger
2. Secure the bracket to the charger using 4x6mm screws provided, make sure the bracket retains the USB cable in place.
3. Optionally screw the bracket to the desk using the 15mm screw provided. The screw hole is located near the USB cable retainer.

2. Bracket secured via lanyard.

1. Plug USB cable into the charger
2. Secure the bracket to the charger using 4x6mm screws provided, make sure the bracket retains the USB cable in place.
3. Attach the lanyard to the bracket using the short, 3mm, grub screw. The fixing point is located near the USB cable retainer.
4. Attach the other end of the lanyard as required to a suitable location on the furniture using the 15mm screw and wall fixing plug provided.

3. Adhesive pad.

1. Plug USB cable into the charger
2. If you want to use the bracket to secure the USB cable then attach the bracket to the charger using 4x6mm screws provided.
3. Remove the protective paper from one side of the sticky pad and carefully position the pad on the bracket (if fitted) or directly on the base of the charger.
4. Remove the other protective paper from the other side of the adhesive pad and place as required on the surface. Note once stuck to the surface it may not be easy to remove, so make sure you have positioned as required.

4. Free standing.

1. Plug USB cable into the charger
2. If you want to use the bracket to secure the USB cable then attach the bracket to the charger using 4x6mm screws provided.

When you have mounted the wireless charger, plug the cable into the power adapter and then plug the adapter into a suitable wall outlet. The indicator should blink blue/red twice.

Usage

Simply place a compatible device on the charger so the indicator turns blue. When the device is fully charged the indicator will turn off.

In the case of an error or foreign object the indicator flashes red. Remove the device or foreign object so the red flashing light goes off.

Indicator	Meaning
Blue/red flash twice	Power up sequence completed.
Blue	Device charging
Off	Device charging completed.
Red flashing	Foreign object detected or other error.

Specifications

Power Input:	Micro-USB QC3.0 (5V/2A,9V/1.8A)
Wireless Output:	5/7.5/10W (phone dependent).
Switching Frequency:	110KHz-205KHz
Operating Temperature Range:	0~35°C
Storage Temperature Range:	-20 ~ 70°C
Operation Humidity:	10% ~ 80% RH
Storage Humidity:	5% ~ 95% RH
Size (excluding bracket):	104.8mm (Dia.) * 14.5mm (H)

Visit our website at: www.teleadapt.com

TA-8200-US-A00, 10W On-Desk Wireless Charger User Manual.
Revision 16, 2022-07-28.
All rights reserved. All copyrights and trademarks acknowledged.
Specifications subject to change without notice.