

ChargePort Qi2 | TA-8205



Table of Contents

Introduction	2
Package Contents	2
Part Numbers	3
Important Safety Instructions	3
Mounting and Installation	4
Usage	5
Specifications	5

Introduction

Thank you for purchasing the ChargePort Qi2. Please read these instructions carefully before using this product and keep this manual for future reference.

The new ChargePort Qi2 conforms to the Qi v2.0 standard from the WPC (Wireless Power Consortium).

Supporting wireless charging up to 15 watts, the ChargePort Qi2 is compatible with phones that conform to both Magnetic Power Profile (MPP) or also Basic Power Profile (BPP).

ChargePort Qi2 employs a unique folding design. When extended using an MPP phone allows 15W charging with the phone retained by magnets. If your phone does not support MPP then the ChargePort Qi2 can be folded flat to allow charging using the BPP profile.

The ChargePort Qi2 is ideal for hotel usage and comes complete with a USB cable, power supply, security bracket and adhesive pad.

The ChargePort Qi2 is Qi Certified and FCC/CE/UKAS compliant.

Package Contents

- ChargePort Qi2 Wireless Charger unit, black.
- Wall charger with US, UK or EU plug (model dependent).
- USB Type-C cable, 1.5M, black.
- Mounting bracket with screws.
- 3M double sided adhesive pad, black.
- Rubber pad (with one adhesive side).
- Security lanyard with screws.
- Installation Guide.

Part Numbers

TA-8205-US-B00	On-Desk Qi2.0 wireless charger(15W), with US PSU, black
TA-8205-EU-B00	On-Desk Qi2.0 wireless charger(15W), with EU PSU, black
TA-8205-UK-B00	On-Desk Qi2.0 wireless charger(15W), with UK PSU, black

Important Safety Instructions

- Always use the wireless charger in accordance with the instructions in this user manual.
- Use the supplied power adapter and USB cable.
- Unplug the wireless charger after use.
- Do not use the wireless charger with devices that are not Qi Certified.
- It is normal that the wireless charger may get a little warm during use.
- The wireless charger will not charge any devices that do not conform to the Qi specification. In this case remove the non-conformant device.
- Do not install wireless charger close to a heat source such as a radiator or in direct sunlight.
- Do not expose the wireless charger near sources of liquid like a sink, basin, bath or shower.
- Do not use corrosive or abrasive cleaners on the wireless charger.

Mounting and Installation

Choose the mounting option that best meets your needs. Make sure you mount within reach of a suitable mains outlet so the power supply cable is not over extended.

1. Bracket secured to desk.

1. Plug the USB cable into the charger
2. Secure the bracket to the charger using screws provided, make sure the bracket retains the USB cable in place.
3. Optionally attach the bracket to the desk using the screw provided. The screw hole is located near the USB cable retainer.

2. Bracket secured via lanyard.

1. Plug USB cable into the charger
2. Secure the bracket to the charger using screws provided, make sure the bracket retains the USB cable in place.
3. Attach the lanyard to the bracket using the short grub screw. The fixing point is located near the USB cable retainer.
4. Attach the other end of the lanyard as required to a suitable location on the furniture using the screw provided and a wall fixing plug.

3. Adhesive pad.

1. Plug USB cable into the charger
2. If you want to use the bracket to secure the USB cable then attach the bracket to the charger using screws provided.
3. Remove the protective paper from one side of the sticky pad and carefully position the pad on the bracket (if fitted) or directly on the base of the charger.
4. Remove the other protective paper from the other side of the adhesive pad and place as required on the surface. Note once stuck to the surface it may not be easy to remove, so make sure you have positioned the unit as required.

4. Free standing.

1. Plug USB cable into the charger
2. If you want to use the bracket to secure the USB cable then attach the bracket to the charger using screws provided.
3. Remove the protective paper from the adhesive side of the rubber pad and carefully stick the rubber pad to the base (or bracket if fitted).

When you have mounted the wireless charger, plug the cable into the power adapter and then plug the adapter into a suitable wall outlet.

Usage

If the device to be charged is MPP (Magnetic Power Profile) compatible then extend the charging pad to its vertical position to charge. The magnets will align and hold the device to be charged in the optimal position. Leave until the device indicates it is fully charged.

MPP devices can also be charged when the charging pad is stowed in the horizontal position in the base.

If the device to be charged is not MPP compatible then simply place the device on the charger when it is stowed in the horizontal position in the base. Leave until the device indicates it is fully charged.

Specifications

Power Input:	USB Type-C (5V/3A,9V/2.22A)
Wireless Output:	5/15W (phone dependent).
Switching Frequency:	128KHz-360KHz
Operating Temperature Range:	0~35°C
Operation Humidity:	10% ~ 90% RH
Magnetic Force	7.6~12N
Protection	OVP, UVP
Size (excluding bracket):	90.07 × 89.93 × 24.1mm

Visit our website at: www.teleadapt.com

TA-8205-xx-A00, ChargePort Qi2.
Revision 27, 2024-07-24.

All rights reserved. All copyrights and trademarks acknowledged.
Specifications subject to change without notice.