

Godox 神牛

LED Video Light

LEDM150 Mini LED Video Light  
迷你LED摄影灯



深圳市神牛摄影器材有限公司

GODOX Photo Equipment Co., Ltd.

地址/Add: 深圳市宝安区福永镇福洲大道西新和村华发工业园A4栋

Building A4, Xinhe Huafa Industrial Zone, Fuzhou RD West, Fuyong

Town, Baoan District, Shenzhen 518103, China

电话/Tel: +86-755-29609320(8062) 传真/Fax: +86-755-25723423

邮箱/E-mail: godox@godox.com

http://www.godox.com

705-LE1500-00

Made In China

FC CE RoHS

Instruction Manual | 说明手册  
Chinese English Bilingual | 中英文双语

型号: LEDM150

## 一、前言

感谢您购买神牛产品！

LED M150迷你摄影灯非常适用于微距拍摄、婚庆拍摄、采访布光、静物拍摄以及手机视频拍摄等。亮度高，轻巧便携，操作简单。

主要特点：

- 150颗高质量高亮度灯珠
- 内置锂电池供电，非常便携
- 光线柔和，整体分布均匀
- 配L型座
- 适用于各品牌摄像机、相机和手机

## ⚠ 警告

- ⚠ 请保持干燥：请勿用湿手接触产品，亦不可将产品浸入水中或暴露于雨中。
- ⚠ 请勿私自拆卸产品，如产品出现故障须由本公司或授权的维修人员进行检查维修。
- ⚠ 请勿让儿童接触本产品。
- ⚠ 本产品不能防水，在雨天及潮湿环境下请注意防水。
- ⚠ 请勿在化学品、可燃性气体或其他特殊物质附近使用闪光灯，这些物质在特殊情况下可能对闪光灯发出的瞬间强光敏感，有可能导致火灾或电磁干扰。在这些场合下，!请注意相关警告标识。
- ⚠ 内置锂电池，禁止拆卸、撞击、挤压或投入火中，若出现严重鼓胀，请勿继续使用。请勿放置在超过50°C的高温环境中。使用专用的充电器进行充电，并且正确的按照操作说明，在规定的电压、温度范围内使用。

## 三、部件

• 主机



## 四、电源管理

### 1. 供电

- 内置大容量锂聚合物电池3.7V/3000mAh。
- LEDM150充满电，最大亮度持续输出约60分钟；电量指示灯能实时反馈电池电量，当电量指示灯闪烁时，请及时充电。



### 2. 充电


- 通过手机充电器连接设备上的USB端口进行充电，时间约4小时(5V1A充电器)。充电时充电状态指示灯亮，充满后指示灯灭。



## 五、使用LED迷你摄影灯

### 1. 手持使用（见图）

- 将L座装进摄影灯的1/4"L座安装孔；
- 扭紧上端热靴固定旋钮。



### 2. 灯架使用（见图）

- 将L座装进摄影灯的1/4"L座安装孔，并扭紧上端热靴固定旋钮。
- 将灯架固定在1/4"L座安装孔上。



### 3. 手机使用（见图）

- 将固定支架从LED迷你摄影灯的右边推进并卡紧，取出固定支架则是按相反的方向推。
- 将手机固定在固定支架上。



## 六、操作说明

### 1、开始使用摄影灯

- 按ON/OFF电源开关，摄影灯开始发光。



### 2、亮度调节

- 旋转主机上的亮度调节旋钮可对亮度进行调节。
- 亮度范围：10%-100%



## 七、标配物品

序号	包含物品	LEDM150
1	LED摄影灯	1个
2	L座	1个
3	柔光罩	1个
4	固定支架	1个
5	USB线	1条



## 八、产品参数

LED灯	LEDM150
内置锂电池供电	3.7V-3000mAh锂电池
功率	最大9W
色温	5600K ±300K
100%光照度 (LUX)	1029 (0.5米)
显色指数	>95
TLCI	≥94
调光范围	10%~100%
灯珠数量	150个
工作环境温度	-10~50°C
产品尺寸	132mm*80mm*20mm (不包含L座和固定支架尺寸)
净重	170g

设计和规格如有变更，恕不另行通知。

# Foreword

Thank you for purchasing this Godox product!

**LED M150** Mini video light is excellent for macrophotography, wedding shooting, product shooting, photojournalistic and video recording, etc. The lightweight and portable light provides high brightness and convenient operation.

## Features:

- High-quality LED bulbs
- Built-in lithium battery with great portability
- Soft light and even illumination
- Included with a L-type bracket
- Fits almost any cameras, camcorders and mobile phones

## ⚠ Warning

- ⚠ Always keep this product dry. Do not use in rain or in damp conditions.
- ⚠ Do not disassemble. Should repairs become necessary, this product must be sent to an authorized maintenance center.
- ⚠ Keep out of reach of children.
- ⚠ As this product do not have waterproof function, please take measures of waterproof in rainy or damp environment.
- ⚠ Do not use the flash unit in the presence of flammable gases, chemicals and other similar materials. In certain circumstance, these materials may be sensitive to the strong light emitting from this flash unit and fire or electromagnetic interference may result.
- ⚠ As this product has built-in lithium battery, do not disassemble, impact, squeeze or put it into fire. If serious bulge occurs, please do not use. Do not use or store the product if the ambient temperature reads over 50°C. Please charge the product with specialized charger and correctly operate it within the defined voltage and working temperate according to the instruction manual.

# Parts

## • Body



# Power Management

## 1. Power Supply

Built-in large capacity lithium battery 3.7V/3000mAh.



- LEDM150 is able to provide the maximum brightness continuously up to 60 minutes when fully charged.

**Note:** The indicator light is to display the battery level, when the light is blinking, please charge in time.

## 2. Charging the Battery

- Insert the mobile phone charger to the USB Port, after 4 hours, the light can be fully charged (with 5V1A charger).

The Status Indicator Lamp lights up when charging and turn off when the battery is fully charged.



# Using the Video Light

## 1. By the Handle

- Install the L-type Bracket onto the 1/4" Bracket Mounting Hole.
- tighten the upper locking ring of the L-type Bracket.



## 2. On the Light Stand

- Install the L-type Bracket onto the 1/4" Bracket Mounting Hole and tighten the upper locking ring of the L-type Bracket.
- Install the light stand onto the 1/4" Bracket Mounting Hole.



## 3. On the Mobile Phone

- Push into and lock the Mounting Bracket from the right direction of the light, pull out from the opposite direction of pushing in.
- Install the Mobile Phone onto the Mounting Bracket.



# Operation

## 1. Before Usage

- Switch the power on, the video light giving out light.




## 2. Light Brightness Adjustment

- Turn the Select Dial for Light Brightness to adjust the light brightness.
- Light Brightness Range: 10%-100%



# What's in the Box of LEDM150?

NO.	Included Item	LEDM150
1	LED Video Light	1 PC
2	L-type Bracket	1 PC
3	Diffuser	1 PC
4	Mobile Phone Mounting Bracket	1 PC
5	USB Cord	1PC



# Technical Data

LED Light	LEDM150
Built-in Lithium Battery	3.7V-3000mAh
Power	Max. 9W
Color Temperature	5600K±300K
Brightness(LUX)	1029 (0.5 m)
Color Rendering Index	>95
TLCI	≥94
Light Brightness Range	10%~100%
LED Beads Quantity	150
Operation Temperature	-10~50°C
Dimension	132mm*80mm*20mm(not with the L-type Bracket and Mounting Bracket)
Net Weight	170g

\* Product design and specifications are subject to change without notice.

## Declaration of Conformity

GODOX Photo Equipment Co.,Ltd. hereby declares that this equipment are in compliance with the essential requirements and other relevant provisions of Directive 2014/30/EU. They are allowed to be used in all EU member states. For more information of DoC, Please click this web link: [http://www.godox.com/DOC/Godox\\_LEDM150\\_DOC.pdf](http://www.godox.com/DOC/Godox_LEDM150_DOC.pdf)