

# GE2500

2.6kVA Petrol Generator

## GENERATOR SPECIFICATION

Voltage	230/115
Phase	1
Frequency	50Hz
Prime Power (PRP)	2.6 kVA / 2.1 kW
Alternator	NSM K80B
Alternator Type	Brushless - Smooth Waveform
Fuel tank capacity	3.1 Litres
Autonomy 75% load	3.1 Hours
LWA	96
dBA @ 7M	71

## ENGINE SPECIFICATION

Engine	Honda GP160
Emissions certified	N/A
Cylinders	Single
Distribution	O.H.V.
Aspiration	Normally aspirated
Cooling	Air
Displacement	163 cm <sup>3</sup>
Rpm	3000
Starting system	Recoil
Fuel	Unleaded 86 octane or higher



## DIMENSIONS (mm)

Length	Width	Height	WEIGHT (KG)
610	420	415	34

**HONDA**  
The Power of Dreams

24 Months Non-Commercial Engine Warranty (Limited)

3 Months Commercial Engine Warranty (Limited)

## CONTROL BOX (Plastic)

- 1 x 16A 230V & 1 x 16A 115V BS4343 sockets.
- Reset circuit breaker overload protection.
- Voltage selector switch.

## STANDARD FEATURES

- Oil alert/low oil shutdown.
- Full wrap-around frame.
- Brushless smooth waveform alternator.

## OPTIONS

- Single voltage.
- Trolley kit.

## POWER DEFINITION

**Prime Power (PRP)** : Applicable for supplying power to varying electrical load for unlimited hours in accordance ISO 8528-1 under the agreed operating conditions with the maintenance intervals and procedures being carried out as prescribed by the manufacturers.