

SW200DC

200Amp DC Welder Petrol Generator

WELDER GENERATOR SPECIFICATION

Welding Output	200 Amps DC
Duty Cycle	35% - 200A / 60% - 170A
Voltage	230/115
Phase	1
Frequency	50Hz
Auxiliary Output	230V @ 4.0 kVA / 3.2 kW 115V @ 4.0 kVA / 3.2 kW
Alternator	Sincro EW200DC
Rod Size (max)	4mm
Alternator Type	Brushed - self regulated
Fuel tank capacity	6.1 Litres
Autonomy 75% load	2.2 Hours
LWA	97
DBA @ 7M	72

ENGINE SPECIFICATION

Engine	Honda GX390
Emissions certified	EU Stage V
Cylinders	Single
Distribution	O.H.V.
Aspiration	Naturally aspirated
Cooling	Air
Displacement	389 cm ³
Rpm	3000
Starting system	Recoil
Fuel	Unleaded 86 octane or higher



DIMENSIONS (mm)

WEIGHT (KG)

Length	Width	Height	86
815	480	620	



CONTROL BOX

- 2 x DIN 32 welding sockets.
- Amp range selector switch.
- Variable rated Amp value switch.
- 115V: 1 x 16A BS4343 sockets.
- 230V: 1 x 16A BS4343 sockets.
- Reset circuit breaker overload protection.

STANDARD FEATURES

- Oil alert/low oil shutdown.
- 3 Year engine warranty (Limited).
- Full wrap-around frame.
- Convenient tray for rods & leads.
- Amp value fine tuning for precise welding.

OPTIONS

- Welding lead sets - 6 or 10 meters.
- Trolley kit.
- Electric start.

