

273.1538 (VED2) as an On-On-On switch

Pin 5- Power In

Pin 2- Link to Pin 4

Pin 1- Power Out (Bottom 'on') -Link to Pin 10 for amber illumination

Pin 3- Power Out (Middle 'on')- No illumination

Pin 6- Power Out (Top 'on') -Link to Pin 8 for green illumination.

Pin 7- Earth

Pin 9- Earth

Ultimately you can make any of the 'on' positions illuminate either colour, by externally linking Pin 8 (green) or Pin 10 (amber) to any of the Power Out Pins. However wiring the switch as above makes the most sense as when the rocker is in the 'on' position it will be covering the LED beneath it, creating the best and most intuitive looking rocker illumination.