

On-Off-On DP Wiring Options

Option 1

This will achieve;

Amber illumination in 'on' position 1

Amber illumination in 'on' position 2

Green illumination with the sidelights.

Pin 1- Power Out 1

Pin 2- Power In

Pin 3- Power Out 2

Pin 7- Earth

Pin 8- Sidelight

Pin 9- Earth

Pin 10- Link to Pin 3 and Pin 1

Option 2

This will achieve;

Green illumination in the 'on' position controlled by power out 1

Amber illumination in the 'on' position controlled by power out 2

The switch would not illuminate at all when off.

Pin 1- Power Out 1

Pin 2- Power In

Pin 3- Power Out 2

Pin 7- Earth

Pin 8- Link to Pin 1

Pin 9- Earth

Pin 10- Link to Pin 3

Option 3

This will achieve;

Amber illumination in 'on' position 1

Green illumination with the sidelights

No illumination in 'on' position 2

Pin 1- Power Out 1

Pin 2- Power In

Pin 3- Power Out 2

Pin 7- Earth

Pin 8- Sidelight

Pin 9- Earth

Pin 10- Link to Pin 1

Option 4

This will achieve;

Amber illumination in 'on' position 2

Green illumination with the sidelights

No illumination in 'on' position 1

Pin 1- Power Out 1

Pin 2- Power In

Pin 3- Power Out 2

Pin 7- Earth

Pin 8- Sidelight

Pin 9- Earth

Pin 10- Link to Pin 3